

DMX INSTRUCTIONS

The Power Pack uses 1 channel of DMX, and does not dim. This means that the output will always be at full. It simply acts as a DMX controlled power switch. Using the buttons below the control screen, set to the desired DMX address.

DMX VALUE	FUNCTION
000 - 128	OUTLET OFF
129 - 255	OUTLET ON

THIS UNIT USES 1 CHANNEL OF DMX

TECHNICAL SPECIFICATIONS

POWER

- 110-120v AC input
- 10A Max Passthrough (1200w)

SIZE

- See dimensions below

WEIGHT

- 1lb 4oz

NOTES

- Unit must be grounded (earthed)
- Keep dry, do not use in moist environments
- Unit should not be opened
- Do not use if unit appears damaged

